



Notes : As each final selector is taken into use, the B relay earth operates the busying relay which holds to the P1 earth  
 This keeps the final selectors busied after use until the third final selector is taken into use  
 The P wire earth from the third final selector operates its busying relay which in turn releases all free final selectors 1 - 3  
 The sequence then starts again  
 This arrangement generally ensures that follow on calls do not use the same final selector  
 and that a faulty final selector will not be able to isolate the exchange during light usage  
 Whilst the third final selector is in use or artificially busied, relays 1-2 cannot hold and therefore the finals will no longer be taken into use sequentially

**Final Selector  
 P Wire Busing Relays  
 For Rack A1**